



Application Note

Document Number **APL-L0006**

Updated 08/03/2007 **Rev. A**

Upgrading the software in a AQ2201/AQ2202 Frame Controller

Benefits of using this application

Upgrading the firmware in the AQ2201 or AQ2202 Controller provides upgraded features and bug fixes. It also establishes the version operated by technical support. The firmware is provided free of charge on our Y-Link site to any registered user.

Purpose/Description

This procedure is to provides detailed instructions on how to upgrade the firmware in the AQ2201 and AQ2202 Controller

Upgrading the firmware in The AQ 2200 Controller

1. Insert Compact flash card containing the new firmware into the slot in the rear of the controller.
2. Power the unit on

3. If there is a module in the controller Press the SYSTEM button on the front panel of the controller. This will bring up the same screen as you would get if there was no module in the unit.
4. Arrow down to Update
5. Press the OK soft key
6. Highlight Main Frame
7. Press the OK soft key
8. Arrow up to CF (compact flash)
9. Press the OK soft key
10. The screen will show Ver X.XX to Ver 6.01.04
11. Press the start soft key
12. The unit will be upgraded and will show Done when it is finished.
13. Power down the controller.
14. Remove the Compact Flash Card
15. Power the unit back up